

Installation Manual Home Controller

For questions or clarifications write to us at support@inoho.com

16th March 2015

Install Home Controller

- 1. Power on the home controller
 - Red light should now turn on
 - Green light should start blinking in ~1 min



- 3. Connect the home controller to your WiFi router with the LAN cord.
 - Green should light up and blink intermittently



Access Home Controller via Mobile Devices

1. Download Inoho app, and open it







To be launched in Jul 2015, if not earlier

(android beta available)

If you're unable to access the home controller through the app, refer to page 04 to access via a desktop

Access Home Controller via Desktops

Ensure that your PC/laptop is connected to the home WiFi network.

- 1. Identify the Default Gateway of your router (aaa.bbb.ccc.ddd)
 - **Windows:** Open command prompt (type 'cmd' in run), then type in 'ipconfig'
 - Mac: Open terminal (Applications/ Utilities/Terminal), then type 'netsat -nr'
- 2. Open any browser (Chrome/Firefox etc.) and go to aaa.bbb.ccc.123 ; e.g.

Default gateway	inoho address
aaa.bbb.ccc.ddd	aaa.bbb.ccc.123
192.168.1.1	192.168.1.123
10.0.0.254	10.0.0.123

If you're unable to access the app, refer pg05

Note: You can also use the IP / address to access inoho on your smartphone browser

If you cannot access inoho app

You'll need to disable one of both of the following in your **router settings.**By default, most routers have these disabled

- Disable 'secondary IP address for LAN' so that devices on wifi (phone/laptop) can identify the devices on LAN (home controller)
 - Look for 'secondary LAN IP address'/
 'second IP address and subnet mask for LAN' /something similar
- 2. **Disable** access point isolation so that devices on wifi can talk to devices on LAN

After you've sorted the above two issues, try accessing the home controller again.

Configure Cloud Settings

- 1. Click menu ≡ and select 'Cloud Settings'
- 2. Enter details and select 'Confirm'.

Notes

- 1. It's not necessary to configure cloud settings
- 2. If you've already configured these, entering new details will overwrite the previous settings.

